







# **Model Number**


NCN3-F25F-N4-Y41364


# Connection

N4



# **Dimensions**





# **Technical Data**

General	specifications
---------	----------------

Switching element function		DC	Dual NC	
Rated operating distance	s <sub>n</sub>	3 mm		
Installation		not emb	eddable	
Assured operating distance	sa	0 2.43	3 mm	
Reduction factor r <sub>Al</sub>		0.5		
Reduction factor r <sub>Cu</sub>		0.4		
Reduction factor r <sub>V2A</sub>		1		

## Nominal ratings

Nominal voltage	$U_o$	8 V
Switching frequency	f	0 1500 Hz
Hysteresis	Н	tvp. 5 %

Reverse polarity protected reverse polarity protected

Short-circuit protection yes

Suitable for 2:1 technology yes , reverse polarity protection diode not required Current consumption

LED, yellow

## **Ambient conditions**

# Mechanical specifications

Indication of the switching state

Connection type MINI-COMBICON Housing material PBT

Sensing face PBT
Protection degree IP60
Note Please use Phönix FK-MCP 1,5/4-ST-3,81 connector

General information
Use in the hazardous area see instruction manuals

Category 1G; 2G

## Compliance with standards and directives

Standard conformity

NAMUR EN 60947-5-6:2000 IEC 60947-5-6:1999 Standards EN 60947-5-2:2007 IEC 60947-5-2:2007

# Approvals and certificates

FM approval

Control drawing 116-0165F

UL approval cULus Listed, General Purpose CSA approval cCSAus Listed, General Purpose

www.pepperl-fuchs.com

#### ATEX 1G

Instruction

Device category 1G

Directive conformity

Standard conformity

CE symbol

Ex-identification

EC-Type Examination Certificate

Appropriate type

Effective internal capacitance Ci

Effective internal inductance La

General

Highest permissible ambient temperature

Installation, Comissioning

Maintenance

Special conditions

Protection from mechanical danger

Electrostatic charging

#### Manual electrical apparatus for hazardous areas

for use in hazardous areas with gas, vapour and mist 94/9/EG

EN 60079-0:2006, EN 60079-11:2007, EN 60079-26:2007 Ignition protection "Intrinsic safety"

Use is restricted to the following stated conditions

**C**€0102

⟨ы⟩ II 1G Ex ia IIC T6

TÜV 99 ATEX 1479 X

NCN3-F25.-N4-Y41364

 $\leq$  100 nF A cable length of 10 m is considered.

The value is applicable for the sensor circuit.

 $\leq$  100  $\mu$ H A cable length of 10 m is considered. The value is applicable for the sensor circuit.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual.

The EC-Type Examination Certificate has to be observed. The special conditions

Directive 94/9/EG and hence also EC-Type Examination Certificates apply in general only to the use of electrical apparatus under atmospheric conditions.

The use in ambient temperatures of > 60 °C was tested with regard to hot surfaces

by the mentioned certification authority.

If the equipment is not used under atmospheric conditions, a reduction of the permissible minimum ignition energies may have to be taken into consideration.

The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate. Note: Use the temperature table for category 1 !!! The 20 % reduction in accordance with EN 1127-1:2007 has already been accounted for in the temperature table for category 1.

Laws and/or regulations and standards governing the use or intended usage goal must be observed.

The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety.

The associated apparatus must satisfy the requirements of category ia. Due to the possible danger of ignition, which can arise due to faults and/or transient currents in the equipotential bonding system, galvanic isolation of the power supply and signal circuit is preferable. Associated apparatus without electrical isolation must only be used if the appropriate requirements of IEC 60079-14 are met.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

When used in the temperature range below -20 °C the sensor should be protected from knocks by the provision of an additional housing.

When used in group IIC non-permissible electrostatic charges should be avoided on the plastic housing parts.

**PEPPERL+FUCHS** 

## ATEX 2G

Instruction

# Device category 2G

Directive conformity Standard conformity

CE symbol

Ex-identification

EC-Type Examination Certificate

Appropriate type

Effective internal capacitance Ci

Effective internal inductance Li

General

Highest permissible ambient temperature

Installation, Comissioning

Maintenance

## Special conditions

Protection from mechanical danger

#### Manual electrical apparatus for hazardous areas

for use in hazardous areas with gas, vapour and mist 94/9/FG

EN 60079-0:2006, EN 60079-11:2007
Ignition protection "Intrinsic safety"
Use is restricted to the following stated conditions

€ 0102

⟨Ex⟩ II 1G Ex ia IIC T6

TÜV 99 ATEX 1479 X

NCN3-F25.-N4-Y41364

 $\leq$  100 nF ; a cable length of 10 m is considered. The value is applicable for the sensor circuit.

 $\leq 100~\mu H$  ; a cable length of 10 m is considered. The value is applicable for the sensor circuit.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to!

be observed. The special conditions must be adhered to!
Directive 94/9/EG and hence also EC-Type Examination Certificates apply in general only to the use of electrical apparatus under atmospheric conditions.

The use in ambient temperatures of > 60 °C was tested with regard to hot surfaces by the mentioned certification authority.

If the equipment is not used under atmospheric conditions, a reduction of the permissible minimum ignition energies may have to be taken into consideration.

The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate.

Laws and/or regulations and standards governing the use or intended usage goal must be observed. The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

When used in the temperature range below -20 °C the sensor should be protected from knocks by the provision of an additional housing.

www.pepperl-fuchs.com