


Dimensions

Technical Data

- Stainless steel housing
- Usable up to SIL2 acc. to IEC 61508






Pinout



Wire colors in accordance with EN 60947-5-6

181114_eng.xml	1 2		BN BU	(brown) (blue)
Release date: 2013-02-08 16:53 Date of issue: 2013-02-08 181114_eng.xml	_			
	Acc	ess	ories	
	V1-W 4-pin, M12 female field-attachable connector V1-G 4-pin, M12 female field-attachable connector			



General specifications NAMUR, NC Switching element function Rated operating distance Installation s_n 8 mm non-flush Output polarity NAMUR Assured operating distance Reduction factor r_{Al} 0 ... 6.48 mm 0.42 Sa Reduction factor r_{Cu} 0.4 Reduction factor r₃₀₄ 0.72 Nominal ratings Nominal voltage 8.2 V (R_i approx. 1 kΩ) U_{o} Switching frequency 0 ... 300 Hz 1 ... 15 typ. 5 % Hysteresis Reverse polarity protection Н reverse polarity protected Short-circuit protection yes Current consumption Measuring plate not detected ≥ 3 mA Measuring plate detected ≤1 mA Multihole-LED, yellow Switching state indication Ambient conditions -25 ... 100 °C (-13 ... 212 °F) -40 ... 100 °C (-40 ... 212 °F) Ambient temperature Storage temperature Mechanical specifications Connection type Device connector M12 x 1 , 4-pin Core cross-section Housing material Stainless steel 1.4305 / AISI 303 Sensing face PBT IP67 Protection degree General information see instruction manuals 1G; 2G; 1D Use in the hazardous area Category Compliance with standards and directives Standard conformity NAMUR EN 60947-5-6:2000 IEC 60947-5-6:1999 NE 21:2007 Electromagnetic compatibility Standards EN 60947-5-2:2007 IEC 60947-5-2:2007 Approvals and certificates FM approval 116-0165F Control drawing UL approval cULus Listed, General Purpose CSA approval cCSAus Listed, General Purpose CCC approval Products with a maximum operating voltage of \leq 36 V do not bear a CCC marking because they do not require approval.

Subject to modifications without notice Pepperl+Fuchs Group

USA: +1 330 486 0001 www.pepperl-fuchs.com fa-info@us.pepperl-fuchs.com

Copyright Pepperl+Fuchs Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



1

ATEX 1G					
Instruction	Manual electrical apparatus for hazardous areas				
Device category 1G	for use in hazardous areas with gas, vapour and mist				
Directive conformity	94/9/EG				
Standard conformity	EN 60079-0:2009, EN 60079-11:2007, EN 60079-26:2007 Ignition protection "Intrinsic safety" Use is restricted to the following stated conditions				
CE marking	C€ 0102				
Ex-identification	🐼 II 1G Ex ia IIC T6 Ga				
EC-Type Examination Certificate	PTB 00 ATEX 2048 X				
Appropriate type	NCN8-18GMN0				
Effective internal capacitance Ci	\leq 95 nF ; a cable length of 10 m is considered.				
Effective internal inductance L _i	\leq 100 μH ; a cable length of 10 m is considered.				
General	The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to! Directive 94/9/EG and hence also EC-Type Examination Certificates apply in general only to the use of electrical apparatus under atmospheric conditions. The use in ambient temperatures of > 60 °C was tested with regard to hot surfaces by the mentioned certification authority. If the equipment is not used under atmospheric conditions, a reduction of the permissible minimum ignition energies may have to be taken into consideration.				
Highest permissible ambient temperature	The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate. Note: Use the temperature table for category 1 !!! The 20 % reduction in accordance with EN 1127-1:2007 has already been accounted for in the temperature table for category 1.				
Installation, Comissioning	Laws and/or regulations and standards governing the use or intended usage goal must be observed. The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety. The associated apparatus must satisfy the requirements of category ia. Due to the possible danger of ignition, which can arise due to faults and/or transient currents in the equipotential bonding system, galvanic isolation of the power supply and signal circuit is preferable. Associated apparatus without electrical isolation must only be used if the appropriate requirements of IEC 60079-14 are met.				
Maintenance	No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.				
Specific conditions					
Protection from mechanical danger	When used in the temperature range below -20 $^\circ\mathrm{C}$ the sensor should be protected from knocks by the provision of an additional housing.				
Electrostatic charging	Electrostatic charges must be avoided on the mechanical housing components. Dangerous electrostatic charges on the mechanical housing components can be avoided by incorporating these in the equipotential bonding.				

Subject to modifications without notice

Germany: +49 621 776-4411 fa-info@pepperl-fuchs.com Copyright Pepperl+Fuchs Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



ATEX 2G

Instruction

Device category 2G Directive conformity Standard conformity

CE marking

Ex-identification

EC-Type Examination Certificate Appropriate type Effective internal capacitance C_i Effective internal inductance L_i General

Highest permissible ambient temperature

Installation, Comissioning

Maintenance

Specific conditions Protection from mechanical danger

Electrostatic charging

Manual electrical apparatus for hazardous areas

for use in hazardous areas with gas, vapour and mist 94/9/EG EN 60079-0:2009, EN 60079-11:2007 Ignition protection "Intrinsic safety" Use is restricted to the following stated conditions $C \in$ 0102

🐼 II 1G Ex ia IIC T6 Ga

PTB 00 ATEX 2048 X

NCN8-18GM ...- N0 ...

 \leq 95 nF ; a cable length of 10 m is considered.

 \leq 100 μ H ; a cable length of 10 m is considered.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to!

Directive 94/9/EG and hence also EC-Type Examination Certificates apply in general only to the use of electrical apparatus under atmospheric conditions. The use in ambient temperatures of > 60 °C was tested with regard to hot surfaces

by the mentioned certification authority. If the equipment is not used under atmospheric conditions, a reduction of the per-

missible minimum ignition energies may have to be taken into consideration.

The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate.

Laws and/or regulations and standards governing the use or intended usage goal must be observed. The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

When used in the temperature range below -20 $^\circ C$ the sensor should be protected from knocks by the provision of an additional housing.

Electrostatic charges must be avoided on the mechanical housing components. Dangerous electrostatic charges on the mechanical housing components can be avoided by incorporating these in the equipotential bonding.

Pepperl+Fuchs Group USA: + www.pepperl-fuchs.com fa-info@us

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com Germany: +49 621 776-4411 fa-info@pepperl-fuchs.com Copyright Pepperl+Fuchs Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



ATEX 1D

Instruction

Device category 1D Directive conformity Standard conformity

CE marking

Ex-identification EC-Type Examination Certificate Appropriate type Effective internal capacitance C_i Effective internal inductance Li General

Maximum housing surface temperature

Installation, Comissioning

Maintenance

Specific conditions

Electrostatic charging

Manual electrical apparatus for hazardous areas

for use in hazardous areas with combustible dust 94/9/EG IEC 61241-11:2002: draft; prEN61241-0:2002 type of protection intrinsic safety "iD" Use is restricted to the following stated conditions €0102

(Ex) II 1D Ex iaD 20 T 108 °C (226.4 °F) ZELM 03 ATEX 0128 X NCN8-18GM...-N0...

 \leq 95 nF; a cable length of 10 m is considered.

 \leq 100 μ H ; a cable length of 10 m is considered.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual.

NCN8-18GM40-N0-V1

The EC-Type Examination Certificate has to be observed.

The special conditions must be adhered to!

The maximum surface temperature of the housing is given in the EC-Type Examination Certificate.

Laws and/or regulations and standards governing the use or intended usage goal must be observed

The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety.

The associated apparatus must satisfy at least the requirements of category ia IIB or iaD. Because of the possibility of the danger of ignition, which can arise due to faults and/or transient currents in the equipotential bonding system, galvanic isolation in the power supply and signal circuits is preferable. Associated apparatus without electrical isolation must only be used if the appropriate requirements of IEC 60079-14 are met.

The intrinsically safe circuit has to be protected against influences due to lightning. When used in the isolating wall between Zone 20 and Zone 21 or Zone 21 und Zone 22 the sensor must not be exposed to any mechanical danger and must be sealed in such a way, that the protective function of the isolating wall is not impaired. The applicable directives and standards must be observed.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

Electrostatic charges must be avoided on the mechanical housing components. Dangerous electrostatic charges on the mechanical housing components can be avoided by incorporating these in the equipotential bonding.

Copyright Pepperl+Fuchs Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

