

селективность устройств защиты

селективность DPX/DPX

Автоматический выключатель, расположенный выше (SEL = LOW)

Автоматический выключатель, расположенный ниже	DPX In (A)	DPX 250 S1 (36 кА) DPX-H 250 S1 (70 кА) DPX-L 250 S1 (70 кА)					DPX 630 S1/S2/Sg (36 кА) DPX-H 630 S1/S2/Sg (70 кА) DPX-H 630 S1/S2/Sg (70 кА)				DPX/DPX-H 1600 S1 (50/70 кА)		DPX/DPX-H 1600 S2.Sg (50/70 кА)		DPX/DPX-H 1600 S1.S2.Sg (50/70 кА)	
		40	63	100	160	250	160	250	400	630	630	800	630	800	1250	1600
DPX	lst. (кА)	3.5	3.5	3.5	3.5	3.5	5	5	5	5	10	10	10	10	15	20
DPX125 (16 кА)	16	3.5	3.5	3.5	3.5	3.5	8	8	8	8	T	T	T	T	T	T
	25	3.5	3.5	3.5	3.5	3.5	8	8	8	8	T	T	T	T	T	T
	40		3.5	3.5	3.5	3.5	6	6	6	6	T	T	T	T	T	T
	63			3.5	3.5	3.5	6	6	6	6	T	T	T	T	T	T
	100				3.5	3.5	6	6	6	6	T	T	T	T	T	T
	125				3.5	3.5	6	6	6	6	T	T	T	T	T	T
DPX125 (25 кА)	16	3.5	3.5	3.5	3.5	3.5	8	8	8	8	T	T	T	T	T	T
	25	3.5	3.5	3.5	3.5	3.5	8	8	8	8	T	T	T	T	T	T
	40		3.5	3.5	3.5	3.5	6	6	6	6	T	T	T	T	T	T
	63			3.5	3.5	3.5	6	6	6	6	T	T	T	T	T	T
	100				3.5	3.5	6	6	6	6	T	T	T	T	T	T
	125				3.5	3.5	6	6	6	6	T	T	T	T	T	T
DPX125 (36 кА)	16	3.5	3.5	3.5	3.5	3.5	8	8	8	8	25	25	T	T	T	T
	25	3.5	3.5	3.5	3.5	3.5	8	8	8	8	25	25	T	T	T	T
	40		3.5	3.5	3.5	3.5	6	6	6	6	25	25	T	T	T	T
	63			3.5	3.5	3.5	6	6	6	6	25	25	T	T	T	T
	100				3.5	3.5	6	6	6	6	25	25	T	T	T	T
	125				3.5	3.5	6	6	6	6	25	25	T	T	T	T
DPX160 DPX250ER (25 кА)	25	3.5	3.5	3.5	3.5	3.5	8	8	8	8	20	20	T	T	T	T
	40		3.5	3.5	3.5	3.5	8	8	8	8	20	20	T	T	T	T
	63			3.5	3.5	3.5	6	6	6	6	20	20	T	T	T	T
	100				3.5	3.5	6	6	6	6	20	20	T	T	T	T
	160					3.5		6	6	6	20	20	T	T	T	T
	250							6	6	6	20	20	T	T	T	T
DPX160 DPX250ER (36 кА)	25	3.5	3.5	3.5	3.5	3.5	8	8	8	8	20	20	T	T	T	T
	40		3.5	3.5	3.5	3.5	8	8	8	8	20	20	T	T	T	T
	63			3.5	3.5	3.5	6	6	6	6	20	20	T	T	T	T
	100				3.5	3.5	6	6	6	6	20	20	T	T	T	T
	160					3.5		6	6	6	20	20	T	T	T	T
	250					3.5		6	6	6	20	20	T	T	T	T
DPX160 DPX250ER (50 кА)	25	3.5	3.5	3.5	3.5	3.5	8	8	8	8	20	20	T	T	T	T
	40		3.5	3.5	3.5	3.5	8	8	8	8	20	20	T	T	T	T
	63			3.5	3.5	3.5	6	6	6	6	20	20	T	T	T	T
	100				3.5	3.5	6	6	6	6	20	20	T	T	T	T
	160					3.5		6	6	6	20	20	T	T	T	T
	250							6	6	6	20	20	T	T	T	T
DPX250 (36 кА)	25	3.5	3.5	3.5	3.5	3.5	8	8	8	8	20	20	T	T	T	T
	40		3.5	3.5	3.5	3.5	8	8	8	8	20	20	T	T	T	T
	63			3.5	3.5	3.5	6	8	8	8	20	20	T	T	T	T
	100				3.5	3.5	6	8	8	8	20	20	T	T	T	T
	160					3.5		8	8	8	20	20	T	T	T	T
	250							6	6	6	20	20	T	T	T	T
DPX250 S1 (36 кА)	40		0.63	1	1.6	2.5	8	8	8	8	20	20	T	T	T	T
	63			1	1.6	2.5	6	6	8	8	20	20	T	T	T	T
	100				1.6	2.5	6	6	8	8	20	20	T	T	T	T
	160					2.5		6	8	8	20	20	T	T	T	T
	250							6	6	6	20	20	T	T	T	T

селективность устройств защиты

селективность DPX/DPX (продолжение)

Автоматический выключатель, расположенный выше (SEL = LOW)

Автоматический выключатель, расположенный ниже	DPX In (A)	DPX 250 S1 (36 кА) DPX-H 250 S1 (70 кА) DPX-L 250 S1 (70 кА)					DPX 630 S1/S2/Sg (36 кА) DPX-H 630 S1/S2/Sg (70 кА) DPX-H 630 S1/S2/Sg (70 кА)				DPX/DPX-H 1600 S1 (50/70 кА)		DPX/DPX-H 1600 S2.Sg (50/70 кА)		DPX/DPX-H 1600 S1.S2.Sg (50/70 кА)	
		40	63	100	160	250	160	250	400	630	630	800	630	800	1250	1600
DPX	Ist. (кА)	3.5	3.5	3.5	3.5	3.5	5	5	5	5	10	10	10	10	15	20
DPX-H/L 250 (70/100 кА)	25	3.5	3.5	3.5	3.5	3.5	8	8	8	8	20	20	30	30	30	36
	40		3.5	3.5	3.5	3.5	8	8	8	8	20	20	30	30	30	36
	63			3.5	3.5	3.5	6	8	8	8	20	20	30	30	30	36
	100				3.5	3.5	6	8	8	8	20	20	30	30	30	36
	160					3.5		8	8	8	20	20	30	30	30	36
DPX-H/L 250 S1 (70/100 кА)	250							6	6	20	20	30	30	30	36	
	40		0.63	1	1.6	2.5	8	8	8	8	20	20	30	30	30	36
	63			1	1.6	2.5	6	6	6	6	20	20	30	30	30	36
	100				1.6	2.5	6	6	6	6	20	20	30	30	30	36
	160					2.5		6	6	6	20	20	30	30	30	36
DPX630 (36 кА)	250								6	6	15	15	20	20	20	T
	320								6	6	15	15	20	20	20	T
	400									6	15	15	20	20	20	T
	500										10	10	20	20	20	T
	630											10	10	20	20	T
DPX-H/L 630 (70/100 кА)	250								6	6	15	15	20	20	20	36
	320								6	6	15	15	20	20	20	36
	400									6	15	15	20	20	20	36
	500										10	10	20	20	20	36
	630											10	10	20	20	36
DPX630 S1/S2/Sg (36 кА)	160							5	5	5	15	15	20	20	20	T
	250								5	5	15	15	20	20	20	T
	400									5	15	15	20	20	20	T
	630										15	15	20	20	20	T
DPX-H/L 630 S1/ S2/Sg (70/100 кА)	160							5	5	5	15	15	20	20	20	36
	250								5	5	15	15	20	20	20	36
	400									5	15	15	20	20	20	36
	630										15	15	20	20	20	36
DPX1250 (50 кА)	500										15	15	20	20	20	20
	630											15	20	20	20	20
	800												20	20	20	20
	1000													20	20	20
	1250														20	20
DPX-H/L 1250 (70/100 кА)	500										15	15	20	20	20	20
	630											15	20	20	20	20
	800													20	20	20
	1000														20	20
	1250															20
DPX/DPX-H 1600 S1 (50/70 кА)	630											15	15	15	20	20
	800													15	20	20
DPX/DPX-H 1600 S2/Sg (50/70 кА)	630											15	15	15	20	20
	800													15	20	20
DPX/DPX-H 1600 S1/S2/Sg (50/70 кА)	1250															20
	1600															20

Предохранитель, расположенный выше

Автоматические выключатели, расположенные ниже	Типа gG		
	250 A	400 A	1000 A
DPX 125	7500		
DPX 160		10000	
DPX 250 ER		10000	
DPX 250		10000	
DPX 630			50000