


# Model Number

NCN3-F25-N4-Y51071


## Features

- · For installation in housing
- Direct mounting on standard actuators
- Satisfies machinery directive
- EC-Type Examination Certificate TÜV99 ATEX 1479X

### Connection



**Dimensions** 



### **Technical Data**

looninoan Bata		
General specifications		
Switching element function		DC Dual NC
Rated operating distance	s <sub>n</sub>	3 mm
Installation		flush mountable
Output polarity		NAMUR
Assured operating distance	sa	0 2.43 mm
Reduction factor r <sub>Al</sub>		0.5
Reduction factor r <sub>Cu</sub>		0.4
Reduction factor r <sub>V2A</sub>		1
Reduction factor r <sub>St37</sub>		1.2
Nominal ratings		
Nominal voltage	Uo	8 V
Switching frequency	f	0 1500 Hz
Hysteresis	Н	typ. 5 %
Reverse polarity protected		reverse polarity protected
Short-circuit protection		yes
Current consumption		
Measuring plate not detected		≥ 3 mA
Measuring plate detected		≤1 mA
Indication of the switching state		LED, yellow
Ambient conditions		
Ambient temperature		-25 100 °C (-13 212 °F)
Storage temperature		-40 100 °C (-40 212 °F)
Mechanical specifications		
Connection type		160 mm PVC cable incl. Binder connector 09-0441-90-04
Core cross-section		0.14 mm <sup>2</sup>
Housing material		PBT
Sensing face		PBT
Protection degree		IP67
Note		Installation in housing
General information		
Use in the hazardous area		see instruction manuals
Category		1G; 2G
Compliance with standards and d	lirective	28
Standard conformity		
NAMUR		EN 60947-5-6:2000
		IEC 60947-5-6:1999
Electromagnetic compatibility		NE 21:2007
Standards		EN 60947-5-2:2007 IEC 60947-5-2:2007
Approvals and certificates		
UL approval		cULus Listed, General Purpose
CSA approval		cCSAus Listed, General Purpose

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com Copyright Pepperl+Fuchs Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



ATEX 1G	
Instruction	Manual electrical apparatus for hazardous areas
Device category 1G	for use in hazardous areas with gas, vapour and mist
Directive conformity	94/9/EG
Standard conformity	EN 60079-0:2006, EN 60079-11:2007, EN 60079-26:2007 Ignition protection "Intrinsic safety" Use is restricted to the following stated conditions
CE symbol	<b>C €</b> 0102
Ex-identification	⟨ II 1G Ex ia IIC T6
EC-Type Examination Certificate	TÜV 99 ATEX 1479 X
Appropriate type	NCN3-F25N4
Effective internal capacitance C <sub>i</sub>	≤ 100 nF A cable length of 10 m is considered. The value is applicable for the sensor circuit.
Effective internal inductance L <sub>i</sub>	$\leq$ 100 $\mu H$ A cable length of 10 m is considered. The value is applicable for the sensor circuit.
Cable length	Dangerous electrostatic charges on the fixed connection cable must be taken into account for lengths equal to and exceeding the following values:
Explosion group IIC	11 cm
General	The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to! Directive 94/9/EG and hence also EC-Type Examination Certificates apply in general only to the use of electrical apparatus under atmospheric conditions. The use in ambient temperatures of > 60 °C was tested with regard to hot surfaces by the mentioned certification authority. If the equipment is not used under atmospheric conditions, a reduction of the permissible minimum ignition energies may have to be taken into consideration.
Highest permissible ambient temperature	The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate. Note: Use the temperature table for category 1 !!! The 20 % reduction in accordance with EN 1127-1:2007 has already been accounted for in the temperature table for category 1.
Installation, Comissioning	Laws and/or regulations and standards governing the use or intended usage goal must be observed. The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety. The associated apparatus must satisfy the requirements of category ia. Due to the possible danger of ignition, which can arise due to faults and/or transient currents in the equipotential bonding system, galvanic isolation of the power supply and signal circuit is preferable. Associated apparatus without electrical isolation must only be used if the appropriate requirements of IEC 60079-14 are met.
Maintenance	No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.
Special conditions	
Protection from mechanical danger	When used in the temperature range below -20 $^\circ\mathrm{C}$ the sensor should be protected from knocks by the provision of an additional housing.
Electrostatic charging	When used in group IIC non-permissible electrostatic charges should be avoided on the plastic housing parts.

Germany: +49 621 776-4411 fa-info@pepperl-fuchs.com

Copyright Pepperl+Fuchs Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



ATEX 2G	
Instruction	Manual electrical apparatus for hazardous areas
Device category 2G	for use in hazardous areas with gas, vapour and mist
Directive conformity	94/9/EG
Standard conformity	EN 60079-0:2006, EN 60079-11:2007 Ignition protection "Intrinsic safety" Use is restricted to the following stated conditions
CE symbol	C € 0102
Ex-identification	€ II 1G Ex ia IIC T6
EC-Type Examination Certificate	TÜV 99 ATEX 1479 X
Appropriate type	NCN3-F25N4
Effective internal capacitance C <sub>i</sub>	$\leq$ 100 nF ; a cable length of 10 m is considered. The value is applicable for the sensor circuit.
Effective internal inductance L <sub>i</sub>	$\leq$ 100 $\mu H$ ; a cable length of 10 m is considered. The value is applicable for the sensor circuit.
General	The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to! Directive 94/9/EG and hence also EC-Type Examination Certificates apply in general only to the use of electrical apparatus under atmospheric conditions. The use in ambient temperatures of > 60 °C was tested with regard to hot surfaces by the mentioned certification authority. If the equipment is not used under atmospheric conditions, a reduction of the permissible minimum ignition energies may have to be taken into consideration.
Highest permissible ambient temperature	The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate.
Installation, Comissioning	Laws and/or regulations and standards governing the use or intended usage goal must be observed. The intrinsic safety is only assured in connection with an appro- priate related apparatus and according to the proof of intrinsic safety.
Maintenance	No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.
Special conditions	

When used in the temperature range below -20  $^\circ\rm C$  the sensor should be protected from knocks by the provision of an additional housing.

#### Special conditions

Protection from mechanical danger

Release date: 2010-11-04 10:17 Date of issue: 2010-11-04 106317\_ENG.xml

 Subject to modifications without notice

 Pepperl+Fuchs Group
 US

 www.pepperl-fuchs.com
 fa-info

